Human Presence Sensor
(Tuya Only - Zigbee Model)



Thank you for your purchase.
Read the instructions carefully before using it, we are not responsible for any consequences caused by abnormal operation.

Need to be used with a Tuya Zigbee gateway (sold separatly).
An active Internet connection and Tuya account are needed to install this product.

Product list:
Human presence sensor x1
User manual x1
Double-sided adhesive x1

Product Overview:
Tuya Human Presence Sensor, breaks through the limitations of traditional infrared technology and realizes **"stillness can be sensed"** by 24Ghz millimeter-wave radar for full-area monitoring. Lasts for up to 180 days (10 reports per day). On Off physical switch design. Bring smarter, safer and more convenient solutions for home, commercial space, and other scenarios.

Product : Human Presence Sensor
Wireless Protocol: Zigbee3.0
Battery Type: AAAx3 (not included)
Motion detection range: 0-500cm
Fixed detection range: 0-300cm
Transmission Frequency: 24GHZ
Operating Temperature: -10°C 50°C
Operating Humidity: 10-95%RH

Installation Guide:
If not already done, install your Tuya Gateway (Not included).
Scan the QR code to download the App or search "Tuya Smart" or "Smart Life" in the app store. Complete the registration and log in your Tuya or SmartLife account.

Battery installation :
Push up to remove the base, open the battery compartment cover, load 3xAAA batteries according to the positive and negative markings, close the battery cover.

Physical master switch:
Toggle the button on the back of the sensor to turn on the device.

Zigbee Sensor Connection:
Make sure your Phone is connected to internet for installation.
Open the Smart Life or Tuya app, click on your Zigbee Gateway, click on Add Sub-device, then select Automatic or manual detection for Tuya Human Presence Sensor or Other Sensor and follow the on-screen instructions to continue.

Place the Presence Sensor as close as possible to the Smart Gateway, long press the reset button until the LED indicator flash rapidly and then enter the automatic networking mode, follow the instructions. Set the options parameters and scenarios.

Fixing method : Use double-sided tape to fix the base in the position you want to install, and then the sensor corresponding to the base.

Through APP, access real-time view of the device status, adjust the parameter settings, linkage smart home and so on.

